



**MOUNT RAILS
 TO UNEVEN
 WALLS**

BT8390-WFK5 SYSTEM X™ ADJUSTABLE DEPTH RAIL MOUNTING BRACKET


The BT8390-WFK5 is an adjustable bracket designed to fix BT8390 and BT8393 rails to uneven walls for a level installation. The BT8390-WFK5 is also compatible for pole and column mounting using B-Tech's System 2 and System X mounts. Ideal for DVLED mounting, the bracket features keyhole fixings for a quick installation and an easy to use rail depth adjustment enabling pinpoint accuracy that is required for DVLED installations.

SPECIFICATION

Wall to rear of rail distance	13mm (+/- 5mm)
Dimensions Min.	W: 45mm H: 270mm D: 40mm
Dimensions Max.	W: 45mm H: 270mm D: 50mm
Max load (per pair)	80kg
Brackets supplied per pack	1
Colour	Black

FEATURES


- Designed to allow BT8390 horizontal and BT8393 vertical I rails to be mounted to walls and poles
- Mounts rail 13mm from the wall with a +/-5mm adjustable depth to ensure a flat to the wall installation
- Can also be pole mounted using B-Tech accessory collars
- Keyhole mounting for easy installation
- Easy adjustment of the depth of the rails with the use of the supplied Hex Key
- Integrated adjustment guides help align rails
- All mounting hardware included



Mounts rail 13mm from the wall with a +/-5mm adjustable depth to ensure a flat to the wall installation



Integrated adjustment guides help align rails



Easy adjustment of the depth of the rails with the use of the supplied Hex Key



Can also be pole mounted using B-Tech accessory collars

