





The APart CMR20T is a compact 2-way rectangular built-in speaker. It can be used as a 16 Ohm or 100 Volt loudspeaker. In 16 Ohm use, you can connect up to 4 loudspeakers in parallel on each channel of a standard 4 Ohm amplifier. For 100 Volt use, the CMR20T is equipped with a High Quality 20 watt 100 Volt transformer with several power tappings. These tappings can be selected via a switch that is hidden behind the loudspeaker grill.

The loudspeaker can be used with high ceilings or places where more back ground noise is present. The CMR20T comes with a 5.25" woofer and 1" tweeter and is therefore suited for both background music and microphone calls.

The housing is made of HQ ABS. Because of the treated paper cone and the aluminium grill the speaker can be used in humid environments. Mounting is very easy due to the 4 screws that are hidden behind the speaker grill.

The standard colour is white RAL 9010. As an option the CMR20T can be painted in any RAL colour (Ref; PAINT-CM). Please note that the minimum order quantity for PAINT-CM is 12 pieces.

2-way HiFi Pro

Also available: in-wall back box for CMR20T (Ref; CMRBBi). On-wall back box for CMR20T (Ref; CMRBB).

SPECIFICATIONS ECHNICAL

Type

Woofer 5.25" treated paper cone Tweeter 1" silk dome Impedance 16 Ohm / 100V 2,5 - 5 - 10 - 20 Watts (4k - 2k - 1k - 500 Ohm) Selector on front!

Transfo Power Tappings

RMS Power 16 Ohm **AES Rated** 40 watt

Music - Program 60 watt RMS Power 100 V

AES Rated 20 watt Music - Program 32 watt SPL 1 watt/1 m 92 dB

Frequency Range 60 Hz - 20 kHz

Dispersion @ 1 kHz 180° @ 4 kHz 70°

Dimensions

237 x 170 mm Outside (H x W) Cutout (H x W) 210 x 143 mm Depth 65 mm

Weight 1.3 Kg